Lampu EXIT SAMCOM SLED-X1 001 Single Side







Lampu EXIT SAMCOM SLED-X1 001 Single Side, rancangan ramping, kompak, ringan, rendah konsumsi listrik & terpercaya sebagai lampu emergency exit

Rating: Not Rated Yet
Ask a question about this product

ManufacturerSamcom

Description

Lampu EXIT SAMCOM SLED-X1 001 Single Side, rancangan ramping, kompak, ringan, rendah konsumsi listrik & terpercaya sebagai lampu emergency exit.

Memenuhi standar keamanan COMPLIANCE : SS263-2/A2: 2008, SS563-1:2010, SS563-2/A1:2013, solusi aman dan reliable untuk gedung komersial.

Baca juga produk serupa lainnya Lampu Exit Samcom SLR158 Single Double.

Dipakai untuk berbagai kebutuhan seperti:

- untuk gedung rumah sakit modern;
- sebagai tanda keluar gedung perkantoran;
- untuk area pabrik dan gudang;
- banyak dipakai untuk lampu emergency exit mall terkemuka di perkotaan;
- cocok dipakai untuk stasiun angkutan umum;
- dan berbagai kebutuhan lainnya sesuai fungsi dan kegunaan.

Spesifikasi lampu exit SAMCOM SLED-X1 ini:

1. input voltage: 230Vac 50/60Hz ±10% A:0.34 PF:0.77
2. battery: 2,4V 2,5Ah/4,5Ah high temp rated cadminium cells
3. lamp used: 1.8w SMT Nichia white LED or T5 white LED tube > 50.000 hrs
4. rated period: >2hrs, 3hrs
5. mode: maintained
6. power consumption: <4VA
7. charge monitor: Ø5mm bi-colour LED (green: normal / red: fault)
8. recharge period: 16~24h
9. emergency luminance: >8cd/m²
10. electromagnetic field: 17m gause @0.1m
11. charger: hybrid controlled charger
12. protection: low volt cut-out to prevent battery over discharge
13. contruction: electrode galvanished sheet steel with epoxy powder coating 20mm ØK/O hole
14. feature: fire retardant acrylic opal diffuser
15. dimension: 475(L)*92(W)*270(H) mm
16. weight: 2,70kg (nett) / 2,80kg (gross)
17. compliance: SS263-2/A2-2008, SS563-1-2010x SS563-x/A1-2013

Reviews

There are yet no reviews for this product.